

IP-CROR | Clean Room Intercom Station

Part No: 1008415000

User Instructions

Making a Direct “One-to-One” Call

- Dial the number of the station you wish to call, **or** press a programmed **DAK** (Direct Access / Speed Dial) key.
- This will send a call request. The receiving station will behave according to its settings:

Open Mode

- The call opens automatically into hands-free two-way communication.
- No action is required by the receiving staff member.

Private Mode

- The receiving station will ring.
 - The staff member must press the “**M**” key to answer the call.
-

Making an “All Call” Announcement

- Dial **84**, or press a programmed **DAK** key for **ALL CALL**.
- A chime will sound.
- After the chime, **press and hold the “M” key** while speaking your announcement.
- Release the “M” key when finished.

Direct Staff Response – Dial 99

If you need a specific individual to respond directly, ask them to dial **99** from any station. This will immediately connect their station to yours for direct communication.

Calling a “Noisy Area”

- When calling a noisy environment, you may need to **press and hold the “M” key** while speaking.
- Release the “M” key to listen.

Group Call

- Group Calls allow announcements to predefined areas within the system.
 - These groups must be configured by your system administrator or management team.
-

Setting Your Station to Open or Private Mode

1. On the station display, select **Menu**.
2. Scroll using the **UP** or **DOWN** keys to **Auto Answer**.
3. Choose **ON** (Open Mode) or **OFF** (Private Mode) using the UP/DOWN keys.
4. Press **Sel**.
5. Press **Back**.
6. When asked to save changes, select **YES**.

